

marantz®

SR6009

AV RECEIVER WITH WIFI & BLUETOOTH



Just as you would expect from any Marantz AV receiver, the new SR6009 pays extra special attention to audio quality, and includes decoders for standard audio as well as for Dolby TrueHD and DTS-HD Master Audio to create a highly immersive and richly detailed surround sound experience. Moreover, with the latest current feedback topology and the Marantz own-developed high-definition HDAMs, the SR6009 has both the power and the finesse to astonish and astound. This seven-channel receiver has the same built-in WiFi, Bluetooth, and DLNA networking facilities as its nine-channel brother, the SR7009 - gapless HD playback, DSD and AIFF streaming, Spotify Connect, Internet radio and AirPlay. Also like its brother, it has Audyssey DSX and DTS Neo:X 7.1 processing, an iPod-digital-compatible USB input and a Phono MM input for vinyl fans. But it's not all about versatility, the SR6009 is also powerful: 185 W for each of its seven channels to be exact. The video section comes with advanced video processing, support of the latest HDMI standard (4k 60Hz pass through / scaling) standard, 7+1 HDMI inputs and dual output for main zone & multi zone. All guarantee complete compatibility with the latest HD displays and HD source devices. It includes the ECO mode and Smart Select as well. This new SR6009 also features a solid aluminium trap door to hide the control buttons and front connections – so it looks as stylish as it sounds. In addition, calibration and optimisation are also quick and easy with the Audyssey MultEQ XT Pro, Setup Assistant and Graphic User Interface overlaid on the picture. Pure enjoyment has never been easier.

Main Features

- Wi-Fi and Bluetooth built in
- Dolby TrueHD and DTS HD Master Audio
- 7ch discrete power amplifier, 185 W per channel
- Current Feedback circuitry with Marantz New HDAM
- Audyssey MultEQ XT room calibration (Pro ready)
- Audyssey DSX; dts-Neo:X (7.1ch)
- Latest HDMI version with 4k 60Hz 4:4:4 resolution
- 7+1 HDMI in / 2 out (4k 60Hz, 4:4:4, 3D, ARC, Deep Color)
- HDMI scaling 1080p, 4k 50/60Hz
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect*, Flickr, Internet Radio support
- Phono (MM) input
- Setup Assistant and advanced GUI
- Trapdoor design; Aluminum front panel
- Marantz Remote App for iOS and Android devices
- ECO mode

EAN

EU	SR6009/N1B	4951035053126	BLACK
	SR6009/N1SG	4951035053133	SILVER-GOLD
UK	SR6009/T1B	4951035053126	BLACK
	SR6009/T1SG	4951035053133	SILVER-GOLD

www.marantz.eu



because music matters

SR6009

AV RECEIVER WITH WIFI & BLUETOOTH



FEATURES	SR6009
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	• / • / • / •
Audyssey DSX	•
dts-Neo:X (7.1ch)	•
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
Photo streaming (JPEG)	•
AirPlay audio streaming	•
Windows PlayTo / Windows 8/RT compatible	• / •
Internet Radio (vTuner) / Spotify Connect *	• / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
CONVENIENT AND SOUND	
FM / AM Tuner	• / •
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
High grade audio components	•
Bluetooth	•
Auto speaker setup by microphone	Audyssey Mult EQ XT (Pro)
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion	CVBS > HDMI; Comp > HDMI
Video processing	>1080p, 4k 50/60Hz
ISF Certification	•
HDMI pass-through on stand-by	•
3D video pass-through / Audio Return Channel	• / •
On Screen Display: Advanced GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, German, French, Spanish, Italian, Dutch, Swedish, Polish, Russian)	•
Smart Select	4 presets
Variable cross over	•
Multiroom zones	2
Optimized Bass Redirection	•

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3+1 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 2 (main + zone)
AUDIO	
Analogue In / Out	5+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (7.2)
Subwoofer Out	2
Zone audio preout	•
7.1 multichannel input	•
OTHERS	
Gold-plated terminals	•
Speaker A / B	•
Height speaker terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting)	•
Multi-Room Speaker Terminal	Surround Back assignable
RS232 control	•
IR Flasher In	•
DC Trigger output	•
Marantz remote bus	•
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
SPECIFICATIONS	
Number of poweramps	7
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	185 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	150 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	110 W
Audio Signal to Noise Ratio	98 dB
GENERAL	
Available colours: Black / Silver-Gold	• / •
System Remote Control	RC025SR
Power Consumption in W	650
Power Consumption No-Sound (ECO ...on/off) in W	50 / 95
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm	440 x 398 x 161
Weight in kg	11.4

* This feature is not available in all countries.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

Design and specifications are subject to change by Marantz without notice.